




Characteristics





- economical aerator, rate of flow 6 l/min
- hygienic flush
- is destined for cold and hot water, temperature is regulated by mixer
- water is flowing as long as hands are in the active range
- water stops flowing after removal of hands from the active range of sensor after adjustable time delay (can be set in range 0,25 - 7,75 s)
- function of automatic water stop after 5 minut of continuous flow
- monitoring of battery capacity (for models with index B)
- START/STOP program
- parameter adjustment using by the remote control SLD 03

Dimensions



Technical Specification

Operating voltage

■ SLU 15 24 V DC
■ SLU 15B 6 V

Power input
■ operating by 24 V DC 13 W

operating by 24 V DC
 operating by 6 V
 5 W

Battery life

4 pcs. AA alkaline batteries approx. 2 years
 AA, 1,5 V, 2700 mAh (100 uses per day)

Active range

■ standard 0,13 - 0,19 m

■ START/STOP program 0,05 - 0,15 m

Recommended flow pressure Rate of flow Water inlet 0,13 - 0,19 m

0,05 - 0,15 m

0,1 - 0,6 MPa

6 l/min. (inf. data)

male thread G 1/2"

Supply Specification

SLU 15 - Supply No. 03150 faucet with mixer and electronics, electromagnetic valve (2 pcs.), connecting hoses, angle valve with filter and check valve (2 pcs.),

4 pcs. AA alkaline batteries 1,5 V, 2700 mAh with battery case (SLU 15B)

Recommended Accessories

SLZ 01Y	-	Supply No. 05012	power supply 24 V DC for operating of max. 2 pcs. of washbasin taps
SLZ 01Z	-	Supply No. 05011	power supply 24 V DC for operating of max. 4 pcs. of washbasin taps
SLZ 04Y	-	Supply No. 05042	power supply 24 V DC for DIN rail, for operating of max. 2 pcs. of washbasin taps
SLZ 04Z	-	Supply No. 05041	power supply 24 V DC for DIN rail, for operating of max. 4 pcs. of washbasin taps
SLZ 04X	-	Supply No. 10049	power supply 24 V DC for DIN rail, for operating of max. 7 pcs. of washbasin taps
SLD 03	-	Supply No. 07030	remote control for an adjustment of parameters
SLA 36	-	Supply No. 06360	set of 4 pcs. alkaline batteries AA, 1,5 V, 2700 mAh (for models with index B)